



JP1	NT/TE settings port X	
	<p>Set all jumpers to the right to select NT mode for port X</p>	<p>Set all jumpers to the left to select TE mode for port X</p>
JP2	Pinout	
	<p>E1 Pinout (1,2,4,5)</p>	<p>S2M Pinout(3,4,5,6)</p>
LED	Status LED	

SW1	Termination of interface port X															
	<p>Right switch: ON Termination 75 Ω</p>	<p>Right switch: OFF Termination 120 Ω</p>														
SW2	Card ID switches															
	Use DIP switches 1 to 2 to set the card ID (very useful for remotely identifying individual cards):															
	<table border="1"> <thead> <tr> <th>Card-ID</th> <th>0</th> <th>1</th> <th>2</th> <th>3</th> </tr> </thead> <tbody> <tr> <td>SW2_1</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> </tr> <tr> <td>SW2_2</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> </tr> </tbody> </table>	Card-ID	0	1	2	3	SW2_1	OFF	ON	OFF	ON	SW2_2	OFF	OFF	ON	ON
Card-ID	0	1	2	3												
SW2_1	OFF	ON	OFF	ON												
SW2_2	OFF	OFF	ON	ON												

CON1	miniPCI connector
	Conenctor for the miniPCI card
CON2	Connector for the RJ45 board
CON3	PCM Connector